FIG. 1



FIG. 2


20
MAD 3
MAD 2
MAD 1
MAD 0
SHFTEN
VSYNC/2
DOTCLK
DISPT
CUDI
Vcc
VSYNC
TEST
INCLK
HSYNC
FA4
FA3
FA5
9
8
7
6
5
4
3
2
1
68
67
66
65
64
63
62
61
MAD 4
MRD
DRAW
AS
MCYC
2CLK
MAD 5
GND A
GND B
MAD 6
MAD 7
MAD 8
MAD 9
MAD 10
MAD 11
MAD 12
MAD 13
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
60
59
58
57
56
55
54
53
52
51
50
49
48
47
46
45
44
FA2
FA6
FA1
FA7
FA0
FA8
FA9
OE
GND B
GND A
RAS
CS
WE
FD2
FD1
FD3
FD0
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
MAD 14
MAD 15
MA 16
MA 17
MA 18
MA 19
VIDEO A
VIDEO B
Vcc
VIDEO C
VIDEO D
BL2IRQ
IRQCLR
FD 4
FD 7
FD 5
FD 6
(CP-68)

FIG. 3a

ITEM	TERMINAL NO.	TERMINAL NAME	INPUT/OUTPUT	FUNCTION
POWER SUPPLY	35,68	Vcc	—	+5V IS SUPPLIED.
	17,18 51,52	Vcc	—	GND IS CONNECTED.
OPERATION CONTROL SIGNAL	65	INCLK	INPUT	BASIC CLOCK OF MIVAC IS INPUTTED.
	66	TEST	INPUT	MIVAC OPERATION IS TESTED. SET THIS TERMINAL TO "LOW" LEVEL.
ACRTC INTERFACE SIGNAL	15	2CLK	OUTPUT	2CLK SIGNAL IS SUPPIED TO ACRTC. THIS SIGNAL IS ASYMMETRIC, NAMELY, HAS DIFFERENT CYCLE LENGTHS IN THE FIRST HALF AND SECOND HALF OF A MEMORY CYCLE.
	14	MCYC	INPUT	MCYC SIGNAL FROM ACRTC IS INPUTTED. MCYC INDICATES "LOW" AND "HIGH" LEVELS WHEN ACRTC IS IN ADDRESS AND DATA CYCLES, RESPECTIVELY.
	12	$\overline{\text{DRAW}}$	INPUT	$\overline{\text{DRAW}}$ SIGNAL FROM ACRTC IS INPUTTED. $\overline{\text{DRAW}}$ INDICATES WHETHER OR NOT ACRTC IS IN THE DRAW CYCLE. $\overline{\text{DRAW}}$ IS "LOW" LEVEL IN THE DRAW CYCLE AND IS "HIGH" LEVEL IN THE OTHER CYCLES.
	11	MRD	INPUT	MRD SIGNAL FROM ACRTC IS INPUTTED. MRD CONTROLS DATA TRANSFER DIRECTION BETWEEN FRAME BUFFER AND ACRTC. WHEN DATA IS READ FROM FRAME BUFFER, "HIGH" LEVEL IS INPUTTED. WHEN DATA IS WRITTEN IN FRAME BUFFER, "LOW" LEVEL IS INPUTTED.
	13	$\overline{\text{AS}}$	INPUT	$\overline{\text{AS}}$ SIGNAL IS INPUTTED FROM ACRTC $\overline{\text{AS}}$ INDICATES PRESENCE OR ABSENCE OF MEMORY ACCESS.
	64	$\overline{\text{HSYNC}}$	INPUT	$\overline{\text{HSYNC}}$ SIGNAL IS INPUTTED FROM ACRTC. UNDER CONDITIONS OF $\overline{\text{HSYNC}}$="LOW" AND $\overline{\text{DRAW}}$="HIGH", IF AS PULSE IS RECEIVED, $\overline{\text{CS}}$ BEFORE $\overline{\text{RAS}}$ REFRESH OPERATION IS CARRIED OUT.
	67	$\overline{\text{VSYNC}}$	INPUT	$\overline{\text{VSYNC}}$ SIGNAL IS INPUTTED FROM ACRTC. RECEIVED $\overline{\text{VSYNC}}$ IS DIVIDED BY TWO SO AS TO OUTPUTTED AS VSYNC/2 SIGNAL AND IS ALSO USED TO CONTROL MULTIPLEXER OF VIDEO OUTPUT.
	2	$\overline{\text{DISP 1}}$	INPUT	$\overline{\text{DISP 1}}$ SIGNAL IS INPUTTED FROM ACRTC. $\overline{\text{DISP 1}}$ INDICATES SCREEN DISPLAY PERIOD. ORDINARILY, SET "1" TO DISPLAY SIGNAL CONTROL (DSC) BIT OF ACRTC.
	1	$\overline{\text{CUD1}}$	INPUT	$\overline{\text{CUD 1}}$ SIGNAL IS INPUTTED FROM ACRTIC. $\overline{\text{CUD 1}}$ IS LOADED WITH "LOW" LEVEL DURING GRAPHIC CURSOR DISPLAY PERIOD.
	6–10 16 19–28	MAD0 –MAD15	INPUT/OUTPUT	MOD0–MAD15 OF ACRTC ARE INPUTTED. THESE SIGNALS ARE USED AS FRAME BUFFER ACCESS ADDRESS IN ADDRESS CYCLE FOR MCYC="LOW", AS DATA INPUT/OUTPUT FOR DATA TRANSFER BETWEEN ACRTC AND FRAME BUFFER IN DATA TRANSFER CYCLE FOR MCYC="HIGH".
	29–32	MA16–MA19	INPUT	FRAME BUFFER ACCESS ADDRESS MA16–MA19 IS INPUTTED FROM ACRTC.

FIG. 3b

ITEM	TERMINAL NO.	TERMINAL NAME	INPUT/OUTPUT	FUNCTION
FRAME BUFFER INTERFACE SIGNAL	50	$\overline{RAS}$	OUTPUT	$\overline{RAS}$ TIMING SIGNAL IS OUTPUTTED FOR DRAM.
	49	$\overline{CS}$	OUTPUT	$\overline{CS}$ TIMING SIGNAL IS OUTPUTTED FOR DRAM.
	48	$\overline{WE}$	OUTPUT	$\overline{WE}$ TIMING SIGNAL IS OUTPUTTED FOR DRAM.
	53	$\overline{OE}$	OUTPUT	$\overline{OE}$ TIMING SIGNAL IS OUTPUTTED FOR DRAM.
	56,58 60,62 63,61 59,57 55,54	FA0-FA9	OUTPUT	MULTIPLEX ADDRESS IS OUTPUTTED FOR DRAM. ADDRESS TO BE MULTIPLEXED VARIES DEPENDING ON VCF0-VCF3 AND VMD0 ATTRIBUTE CODES.
	44,46 47,45 40,42 43,41	FD0-FD7	INPUT/OUTPUT	FD IS 8-BIT INPUT/OUTPUT SIGNAL FOR DATA TRANSFER BETWEEN ACRTC AND FRAME BUFFER AND FOR FETCHING DISPLAY DATA READ FROM FRAME BUFFER. IN A CASE OF ONE MEMORY CHIP, FD0-FD3 ARE USED, WHEREAS IN A CASE OF TWO FOUR MEMORY CHIPS, FD0-FD7 ARE USED.
CRT DISPLAY INTERFACE SIGNAL	3	DOTCLK	OUTPUT	DOTCLK SIGNAL IS DELIVERED BY DIVIDING INCLK SIGNAL AS BASIC INPUT SIGNAL OF MIVAC BY 1, 2 OR 4. DIVISION RATIO IS SET DEPENDING ON VCF0-VCF3 OF ATTRIBUTE CODE.
	33, 34 36, 37	VIDEO A -VIDEO D	OUTPUT	VIDEO A-DSIGNAL IS 4-BIT OUTPUT SIGNAL WHICH IS OBTAINED BY CONVERTING DISPLAY DATA FROM PARALLEL SIGNAL INTO SERIAL SIGNAL BY SHIFT REGISTER OF MIVAC AND WHICH IS DELIVERED DURING DISPLAY PERIOD INDICATED BY SHFTEN OUTPUT. 4-BIT VIDEO SIGNAL IS DETERMINED BY ATTRIBUTE CODE VCF0-VCF3.
	5	SHFTEN	OUTPUT	SHFTEN INDICATES DISPLAY PERIOD OF VIDEO SIGNAL AND IS SET TO "HIGH" LEVEL DURING DISPLAY PERIOD. IN SINGLE ACCESS, $\overline{DISP1}$ FROM ACRTC IS ELONGATED BACKWARD BY ONE CYCLE, AND IN DUAL ACCESS, $\overline{DISP1}$ IS ELONGATED BACKWARD BY TWO CYCLES SO AS TO PRODUCE THIS SIGNAL.
	4	VSYNC/2	OUTPUT	VSYNC/2 SIGNAL IS INPUTTED TO ACRTC. $\overline{VSYNC}$ IS DIVIDED BY TWO FOR PRODUCING THIS SIGNAL.
OTHERS	38	$\overline{BL2IRQ}$	OUTPUT	$\overline{BL2IRQ}$ IS SET BY BLINK2(MA19) INPUTTED IN ATTRIBUTE CYCLE. DURING ATTRIBUTE CYCLE, WHEN BLINK2 IS AT "HIGH" LEVEL, $\overline{BL2IRQ}$ IS SET TO "LOW" LEVEL.
	39	$\overline{IRQCLR}$	INPUT	$\overline{IRQCLR}$ SIGNAL IS USED TO CLEAR $\overline{BL2IRQ}$ SIGNAL. WHEN "LOW" IS INPUTTED TO $\overline{IRQCLR}$, $\overline{BL2IRQ}$ IS CLEARED TO "HIGH" LEVEL.

FIG. 4


MA OUTPUT CONTROL
2000
2001
2002
2003
MAD 0 - MAD 15
MA 16 - MA 19
L
MPX
FA0-FA9
COLUMN ADDRESS COUNTER
AS
MCYC
DRAW
MRD
VSYNC
HSYNC
DISP1
CUD1
2004
MEMORY CONTROL
2005
RAS, CS, OE, WE
2006
STATE DECODER
2007
INCLK
2009
2010
INCLK
2CLK
2CLK GENERATOR
INCLK DIVIDER
DOTCLK
2008
2011
ATTRIBUTE LATCH
VCF DECODER
2012
2013
FD OUTPUT CONTROL
2014
FD0-FD7
2016
2015
INPUT DATA LATCH
READ DATA LATCH
2017
2018
2019
LATCH CONTROL
DISPLAY DATA LATCH
IRQCLR
2020
2021
LATCH
BL2IRQ OUTPUT
BL2IRQ
SHIFTER CLOCK
MULTIPLEXER
VSYNC/2
20201
20202
20203
SHIFTER
SHFTEN
20204
SKEW
CURSOR BLINK
MPX
MASK
VIDEO A-VIDEO D
2022
2023
2024
2025

FIG. 5a

1-CHIP MEMORY



FIG. 5b 2-CHIP MEMORY



FIG. 5c

4-CHIP MEMORY



F I G. 6


2CLK
MCYC
SINGLE ACCESS
DISPI
DRAW
MRD
FD
VIDEO
SHFTEN
DISPLAY
DISPLAY
DISPLAY
DISPLAY
DRAW
DRAW
DRAW
DUAL ACCESS
DISPI
DRAW
MRD
FD
VIDEO
SHFTEN
DISPLAY
DRAW
DISPLAY
DRAW
DRAW
DRAW
DRAW
2MCYC
DISPI
DRAW
MRD
FD
VIDEO
SHFTEN
DISPLAY
DISPLAY
DISPLAY
DISPLAY
DRAW
DRAW
DRAW

FIG. 7



FIG. 11

CUR 1	CUR 0	CURSOR DISPLAY COLOR
0	0	BLACK (VIDEO A - VIDEO D = 0)
0	1	WHITE (VIDEO A - VIDEO D = 1)
1	0	COLOR REVERSION FOR EACH BIT OF VIDEO A - VIDEO D
1	1	COLOR REVERSION FOR EACH BIT OF VIDEO A-VIDEO C (VIDEO D IS KEPT UNCHANGED)

F I G. 8

MA19	BLINK 2	$\overline{BL2IRQ}$ OUTPUT IS SET
MA18	BLINK 1	BLINKING OF GRAPHIC CURSOR IS SET
MA17	SPL 2	NOT USED IN MIVAC
MA16	SPL 1	
MAD 15	HZ 3	
~	~	
MAD 12	HZ 0	
MAD 11	HSD 3	
~	~	
MAD 8	HSD 0	
MAD 7	MUXEN	MULTIPLEXING OF VIDEO OUTPUT IS SET
MAD 6	VMD	DEPTH OF FRAME BUFFER MEMORY IS SET
MAD 5	CUR 1	DISPLAY COLOR OF GRAPHIC CURSOR IS SET
MAD 4	CUR 0	
MAD 3	VCF 3	OPERATION MODE (DISPLAY COLOR, SHIFT AMOUNT OF SHIFT REGISTER, ACCESS MODE, ETC.) OF MIVAC IS SET
MAD 2	VCF 2	
MAD 1	VCF 1	
MAD 0	VCF 0	

FIG. 9

MODE	CRT SCREEN LAYOUT EXAMPLE (DOTS X RASTER)	MAXIMUM FRAME BUFFER CAPACITY (BYTES)	ACRTC OPERATION FREQUENCY (MHz)	MEMORY ACCESS SPEED	HIGH-SPEED DRAWING	NUMBER OF MEMORIES	COLOR/GRADATION	SHIFT AMOUNT (BITS)	MAXIMUM DOT CLOCK FREQ. (MHz)
0	640x200, 350, 400, 480	512K/128K	4.13	480ns/4ACCESSES	—	1		16	33
1	640x200, 480x240, 320x200, 240						4	8	16.5
2	320x200, 240 266x192						16	4	8.25
3	640x200, 350, 400, 480	1M/256K				2	4	16	33
4	640x200, 480x240, 320x200, 240						16	8	16.5
5	640x200, 350, 400, 480	2M/512K				4		16	33
6	640x200, 480x240, 320x200, 240	512K/128K			○	1			16.5
7	320x200, 240 256x192,						4	8	8.25
8	640x200, 350, 400, 480	1M/256K				2		32	33
9	640x200, 480x240, 320x200, 240						4	16	16.5
A	320x200, 240 256x192						16	8	8.25
B	640x200, 350, 400, 480	2M/512K				4	4	32	33
C	640x200, 480x240, 320x200, 240						16	16	16.5
D	640x200, 350, 400, 480	512K/128K		960ns/16ACCESSES	—	1	4	32	33
E	640x200, 480x240, 320x200, 240						16	16	16.5
F	640x200, 350, 400, 480	1M/256K				2		32	33

FIG. 10

MODE	DOT CLOCK FREQUENCY
0, 3, 5, 8 B, D, F	33MHz ~ 11MHz
1, 4, 6, 9 C, E	16.5MHz ~ 5.5MHz
2, 7, A	8.25MHz ~ 2.75MHz

FIG. 12

VMD	MEMORY CHIP EMPLOYED
0	256K × 4BIT DRAM
1	1M × 4BIT DRAM

FIG. 13

MUXEN	VSYNC/2	VIDEO A	VIDEO B
0	0	A	B
	1	A	B
1	0	A	B
	1	C	D

FIG. 14

BLINK 1	GRAPHIC CURSOR DISPLAY
0	NOT DISPLAYED
1	DISPLAYED

FIG. 15a



FIG. 15b



F I G. 16a



INCLK
2CLK
MCYC
HSYNC
DISP1
MRD
DRAW
AS
0 2 4 6 8 10 12 14 16 18 20 22 24 26 28 30 0 2 4 6
6
7
8
9
10
11
12
13
14
15
16
17

F I G. 16b



F I G. 17a


INCLK
2CLK
MCYC
MSYNC
DISPI
MRD
DRAW
AS
0 2 4 6 8 10 12 14 16 18 20 22 24 26 28 30 0 2 4
6
7
8
9
10
11
12
13
14
15
16
17

FIG. 17b


MAD0 - MAD 15
MA16-MA19
CUDI
RAS
CS
OE
FA0-FA9
FD0-FD7
WE
ADDRESS VALID
MAD0-MAD15 DATA VALID
MAD0-MAD7
ADDRESS VALID
CUDI : VALID
COLUMN 3/15
ROW
COLUMN 0 ADDRESS VALID
COLUMN 0 DATA VALID
18
19
20
25
28
26
27
30
29
24
35
36
33
31

FIG. 18a



FIG. 18b



F I G. 19a



INCLK
2CLK
MCYC
HSYNC
DISP1
MRD
DRAW
AS
2 4 6 8 10 12 14 16 18 20 22 24 26 28 30 0 2 4 6
6
7
8
9
10
11
12
13
14
15
16
17

FIG. 19b



FIG. 20a



FIG. 20b



FIG. 21a


0
2
4
6
8
10
12
14
16
18
20
22
24
26
28
30
0
2
4
6
INCLK
2CLK
MCYC
HSYNC
DISPI
MRD
DRAW
AS
6
6
6
6
6
6
7
8
7
8
9
10
11
12
13
14
15
16
17

FIG. 21b



F I G. 22a


INCLK
2CLK
MCYC
HSYNC
DISPI
MRD
DRAW
AS
0 2 4 6 8 10 12 14 16 18 20 22 24 26 28 30 0 2 4 6
6
7
8
9
10
11
12
13
14
15
16
17

FIG. 22b



F I G. 23a


INCLK
2CLK
MCYC
HSYNC
VSYNC
DISPI
MRD
DRAW
AS
6 8 10 12 14 16 18 20 22 24 26 28 30 32 34 36 38 40 42 44 46 48 50 52 54 56 58 60 62 64/0 2 4
VSYNC : VALID
6
7
8
9
10
11
12
13
14
15
16
17

FIG. 23b


MAD0-MAD15
MA16-MA19
CUDI
RAS
CS
DE
FA0-FA9
FD0-FD7
WE
2ND ADDRESS IGNORED
2ND ADDRESS IGNORED
CUDI · VALID
CUDI · VALID
COLUMN 0
COLUMN 1
COLUMN 2
COLUMN 3
COLUMN 4
COLUMN 5
COLUMN 6
COLUMN 7
COLUMN 8
COLUMN 9
COLUMN 10
COLUMN 11
COLUMN 12
COLUMN 13
COLUMN 14
COLUMN 15
COLUMN ADDRESS VALID
COLUMN 15 DATA VALID
COLUMN 3/15 ROW
18
19
20
24
26
27
28
29
30
31
32
33

F I G. 24a



INCLK
2CLK
MCYC
HSYNC
DISP1
MRD
DRAW
AS
0
2
4
6
8
10
12
14
16
18
20
22
24
26
28
30
0
2
4
6
7
8
9
10
11
12
13
14
15
16
17

FIG. 24b


REFRESH
ADDRESS
VALID
22
19
23
MAD 0-
MAD 15
ATTRIBUTE
22
23
MA16-MA19
ATTRIBUTE
20
CUDI
CUDI · VALID
25
24
24
RAS
26
26
CS
OE
FA0-FA9
COLUMN 0/3/15
REFRESH ROW ADDRESS VALID (BUT IGNORED)
FD0-FD7
WE

FIG. 25


INCLK
1
2
3
4
5
INCLK
49
49
DOTCLK
INCLK
49
49
DOTCLK
(DIVIDE BY 2)
INCLK
49
49
DOTCLK
(DIVIDE BY 4)
INCLK
48
48
VSYNC/2
DOTCLK
50
50
VIDEO A
VIDEO D
53
53
SHFTEN

FIG. 26


IRQCLR
DOTCLK
51
52
BL2IRQ

FIG. 27



FIG. 28



FIG. 29a

FA	4 ACCESSES / MCYC (DRAW, DISPLAY)				16 ACCESSES / 2 MCYCS (DISPLAY)			
	256K x 4-BIT (VMDO = 0)		1M x 4-BIT (VMDO = 1)		256K x 4-BIT (VMDO = 0)		1M x 4-BIT (VMDO = 1)	
	ROW	COLUMN	ROW	COLUMN	ROW	COLUMN	ROW	COLUMN
9	—	—	MAD 8	NC0	—	—	MAD 8	NC0
8	MAD 9	NC1	MAD 9	NC1	MAD 9	NC1	MAD 9	NC1
7	MAD 8	NC2	MA 17	MAD 7	MAD 8	NC2	MA 17	MAD 7
6	MAD 7	MAD 6	MA 16	MAD 6	MAD 7	MAD 6	MA 16	MAD 6
5	MAD 15	MAD 5	MAD 15	MAD 5	MAD 15	MAD 5	MAD 15	MAD 5
4	MAD 14	MAD 4	MAD 14	MAD 4	MAD 14	MAD 4	MAD 14	MAD 4
3	MAD 13	MAD 3	MAD 13	MAD 3	MAD 13	MAD 3	MAD 13	MAD 3
2	MAD 12	MAD 2	MAD 12	MAD 2	MAD 12	MAD 2	MAD 12	MAD 2
1	MAD 11	MAD 1	MAD 11	MAD 1	MAD 11	WC1	MAD 11	WC1
0	MAD 10	MAD 0	MAD 10	MAD 0	MAD 10	WC0	MAD 10	WC0

[ ] : COLUMN ADDRESS COUNTER

FIG. 29b

FA	2 ACCESSES / MCYC (DRAW)				4 ACCESSES / MCYC (DISPLAY)				16 ACCESSES / 2MCYCS (DISPLAY)			
	256Kx4-BIT (VMDO=0)		1Mx4-BIT (VMDO=1)		256Kx4-BIT (VMDO=0)		1Mx4-BIT (VMDO=1)		256Kx4-BIT (VMDO=0)		1Mx4-BIT (VMDO=1)	
	ROW	COLUMN	ROW	COLUMN	ROW	COLUMN	ROW	COLUMN	ROW	COLUMN	ROW	COLUMN
9	-	-	MA 18	[NC 0]	-	-	MA 18	[NC 0]	-	-	MA 18	[NC 0]
8	MAD 9	[NC 1]	MAD 9	MAD 8	MAD 9	[NC 1]	MAD 9	MAD 8	MAD 9	[NC 1]	MAD 9	MAD 8
7	MAD 8	MAD 7	MA 17	MAD 7	MAD 8	MAD7	MA 17	MAD 7	MAD 8	MAD 7	MA 17	MAD 7
6	MA 16	MAD 6	MA 16	MAD 6	MA 16	MAD 6	MA 16	MAD 6	MA 16	MAD 6	MA 16	MAD 6
5	MAD 15	MAD 5	MAD 15	MAD 5	MAD 15	MAD 5	MAD 15	MAD 5	MAD 15	MAD 5	MAD 15	MAD 5
4	MAD 14	MAD 4	MAD 14	MAD 4	MAD 14	MAD 4	MAD 14	MAD 4	MAD 14	MAD 4	MAD 14	MAD 14
3	MAD 13	MAD 3	MAD 13	MAD 3	MAD 13	MAD 3	MAD 13	MAD 3	MAD 13	MAD 3	MAD 13	MAD 3
2	MAD 12	MAD 2	MAD 12	MAD 2	MAD 12	MAD 2	MAD 12	MAD 2	MAD 12	[WC 2]	MAD 12	[WC 2]
1	MAD 11	MAD 1	MAD 11	MAD 1	MAD 11	MAD 1	MAD 11	MAD 1	MAD 11	[WC 1]	MAD 11	[WC 1]
0	MAD 10	MAD 0	MAD 10	MAD 0	MAD 10	[WC 0]	MAD 10	[WC 0]	MAD 10	[WC 0]	MAD 10	[WC 0]

[ ] : COLUMN ADDRESS COUNTER

FIG. 29c

FA	1 ACCESSES / MCYC (DRAW)				4 ACCESSES / MCYC (DISPLAY)			
	256K x 4-BIT (VMDO=0)		1M x 4-BIT (VMDO=1)		256K x 4-BIT (VMDO=0)		1M x 4-BIT (VMDO=1)	
	ROW	COLUMN	ROW	COLUMN	ROW	COLUMN	ROW	COLUMN
9	–	–	MA 18	MAD 9	–	–	MA 18	MAD 9
8	MAD 9	MAD 8	MA 19	MAD 8	MAD 9	MAD 8	MA 19	MAD 8
7	MA 17	MAD 7	MA 17	MAD 7	MA 17	MAD 7	MAD17	MAD 7
6	MA 16	MAD 6	MA 16	MAD 6	MA 16	MAD 6	MA 16	MAD 6
5	MAD 15	MAD 5	MAD 15	MAD 5	MAD 15	MAD 5	MAD 15	MAD 5
4	MAD 14	MAD 4	MAD 14	MAD 4	MAD 14	MAD 4	MAD 14	MAD 4
3	MAD 13	MAD 3	MAD 13	MAD 3	MAD 13	MAD 3	MAD 13	MAD 3
2	MAD 12	MAD 2	MAD 12	MAD 2	MAD 12	MAD 2	MAD 12	MAD 2
1	MAD 11	MAD 1	MAD 11	MAD 1	MAD 11	WC1	MAD 11	WC1
0	MAD 10	MAD 0	MAD 10	MAD 0	MAD 10	WC0	MAD 10	WC0

[ ]: COLUMN ADDRESS COUNTER